



DVTech PDA and Mobile remote:

DVTech PDA solution:

1. Browse the DVTech installation CD and open the PDA remote folder.
2. Copy the DVTech PDA Remote file to your memory card in the PDA.
3. Install Microsoft NET framework for PDA or double click on the HTML page located in the PDA folder to open the page.
4. Run the DVTech PDA remote from your PDA.
5. Follow these step to connect to your DVR site:
 - A. Enter the URL or the IP of the DVR system.
 - B. Enter the port number.
 - C. Enter the location name of the DVR system.
 - D. Enter the User name and the password.
 - E. Tick the Direct connect box.
 - F. Click the Connect button to start the connectivity process.

DVTech Mobile solution: (DVTech Mobile solution needs mobiles that support JAVA technology in order to work)

1. Browse the DVTech installation CD and open the Mobile remote folder.
2. Copy the MRemote.jad and MRemote.jar to a folder in the mobile memory.
3. Browse for the folder and choose the MRemote.jad as the installation file.
4. Run the file and validate the installation process.
5. Open the Mobile application menu and browse to DVTech MRemote.
6. When the DVTech mobile remote is open follow these steps:
 - A. Enter the location name of the DVR system
 - B. Enter the IP of the DVR system (if you are using DNS URL enter the www.dvtechone.com address if not enter the IP address.
 - C. Enter the Port number of the DVR system (DNS port is 9999)
 - D. Enter the User name and password (Attention – the user has to be an admin rights user and not a regular one).
 - E. Click on the Connect button to start the connection process.
 - F. Most of the Mobiles will ask to which network you want to connect, please choose one of the networks that you are connecting to the Internet.

The default control buttons are the arrows and the select buttons, in order to change it follow these steps:

1. In the menu choose the options.
2. Choose the configuration option and follow the instructions.

To exit the Mobile remote:

1. In the menu choose the options
2. Choose exit option and wait up to 10 seconds.